State Notation Language and Sequencer Users' Guide

William Lupton (wlupton@keck.hawaii.edu)
W. M. Keck Observatory
Kamuela, HI 96743, USA
March 2000
EPICS Release 3.14.0

Table of Contents

Chapter 1: Introduction

1.1 Note on Versions

Version 1.9 of this manual described version 1.9 of the sequencer and was written by Andy Kozubal, the original author of this software. This version of the manual describes version 2.0, for which the changes have been implemented by William Lupton of W. M. Keck Observatory and Greg White of Stanford Linear Accelerator Center (SLAC).

Version 2.0 differs from version 1.9 mainly in that sequencer run-time code can run under any operating system for which an EPICS OSI (Operating System Independent) layer is available, and message systems other than channel access can be used. It is dependent on libraries which will be generally available only with EPICS R3.14.

An interim version 1.9.4 was made available to the EPICS community; all new developments apart from major bug fixes will be based on version 2.0.

1.2 Overview

The state notation language (SNL) provides a simple yet powerful tool for programming sequential operations in a real-time control system. Based on the familiar state transition diagram concepts, programs can be written without the usual complexity involved with task scheduling, event handling, and input/output programming.

Programs produced by the state notation language are executed within the framework of the run-time sequencer. The sequencer drives the program to states based on events, and establishes interfaces to the program that enable it to perform real-time control in a multi-tasking environment. The sequencer also provides services to the program such as establishing connections to control system variables and handling asynchronous events.

The state notation language and sequencer are components of the Experimental Physics and Industrial Controls System (EPICS). EPICS is a system of interactive applications development tools (toolkit) and a common run-time environment (CORE) that allows users to build and execute real-time control and data acquisition systems for experimental facilities, such as particle accelerators, free electron lasers and telescopes. EPICS is a product of the Accelerator Automation and Controls Group (AOT-8), which is within the Accelerator Operations and Technology (AOT) Division at the Los Alamos National Laboratory. The sequencer interfaces to the underlying control system through a generic PV (process variable) API that supports, among other message systems, the channel access facility of EPICS.

1.3 Content of this Manual

This users manual describes how to use the state notation language to program real-time applications. The user is first introduced to the state notation language concepts through the state transition diagram. Through a series of examples, the user gains an understanding of most of the SNL language elements. Next, the manual explains procedures for compiling and executing programs that are generated by the SNL. Testing and debugging techniques are presented. Then, we present a complete description of the SNL syntax and the sequencer options. Finally, we describe the PV layer, give some examples of working sequences, and describe how to build, test and work with the sequencer installation.

1.4 Copyright and Restrictions

1.5 Notes on This Release

New version 1.9 features have been moved to Section 1.7 on page 5. This section gives brief notes on version 2.0 changes.

Version 2.0 of the sequencer and state notation compiler is available for EPICS release R3.14 and later. We have added several enhancements to the language and to the run-time sequencer. State programs must be compiled under the new state notation compiler to execute properly with the new sequencer. However, under most circumstances no source-level changes to existing programs are required.

1.5.1 Portability changes

These changes allow state programs to run unchanged on hosts and IOCs.

Replaced VxWorks dependencies with OSI routines

All VxWorks routines have been replaced with the appropriate OSI (Operating System Independent) routines. State programs can run in any environment for which there is an OSI implementation.

Unused (and undocumented) **`VX_OPT`** option has been removed.

Replaced direct channel access calls with new PV API

All CA calls have been replaced with equivalent calls to a new PV (process variable) API which can be layered on top of not just CA but also other message systems. See Chapter 6: on page 41.

Added optional generation of main program

The new **`+m`** (main) option generates a C main program whose single argument is a list of macro assignments.

When this option is enabled, the main thread reads from standard input and can execute **`seqShow`**, **`seqChanShow`** *etc.* on demand. End of file causes the sequencer to exit.

1.5.2 New Language Features

Entry handler

A one-off **`entry`** handler can be supplied (*c.f.* the existing **`exit`** handler). This is called once, at sequencer start-up, in the context of the first state set, before the remaining state set threads have been created. See "entry_handler" on page 30.

Entry and exit actions

The **`entry`** block of a state is executed each time the state is entered; the **`exit`** block is executed each time the state is left. Note that these blocks are aassociated with a state and are not the same as the one-off entry and exit handlers. See "entry_action" on page 33 and "exit_action" on page 33.

State options

`-t`, **`-e`** and **`-x`** are now recognized options within the scope of a state. **`-t`** inhibits the "timer reset" on re-entry to a state from itself; **`-e`** (for "entry") is used with the new **`entry`** block, and forces the **`entry`** statements to be executed on all entries to a state, even if from the same state; **`-x`** (for "exit") is complementary to **`-e`**, but for the new **`exit`** block. See "state_option_stmt" on page 33.

Queueable monitors

Monitor messages can be queued and then dequeued at leisure. This means that monitor messages are not lost, even when posted rapidly in succession. This feature is supported by new **`syncQ`**, **`pvGetQ`** and **`pvFreeQ`** language elements, and a new **`seqQueueShow`** routine. When SNL arrays are used, a single queue is shared by the control system variables associated with the elements of the array, which can be useful for parallel control. See "Queuing Monitors" on page 14 and "syncq_stmt" on page 32.

Device support

An device support module has been added. This allows EPICS records to refereerence sequencer internals. At present this is very basic and can only return state-set names. See Section 8.6 on page 61 for a well-hidden example (look for "**`caget ss0`**").

Local variables

SNL does not support the declaration of local variables. However, the C code generated for a **when** clause is now placed within an extra level of braces and the C escape mechanism can be used to declare a local variable. See “Variable Extent” on page 39.

More functions are safe in action code

In previous versions, some functions, *e.g.* **pvPut**, have acquired a resource lock and others, *e.g.* **efTestAndClear**, have not. Those that didn’t were intended for use in action code and those that did not were intended for use in **when** clauses. This was confusing and dangerous. All such functions now acquire a mutex (that can be taken recursively).

Asynchronous puts

pvPut can now put process variables asynchronously by using an extra **ASYNC** argument. Completion can be tested using the new **pvPutComplete**. Arrays are supported (so **pvPutComplete** can be used to test whether a set of puts has completed). See Section 2.13 on page 15 and “pvPutComplete” on page 35.

Synchronous/ asynchronous override on gets and puts

pvGet and **pvPut** both accept an optional **SYNC** or **ASYNC** argument that, for **pvGet**, overrides the default as set using the **-a** option and, for **pvPut**, overrides the default synchronous behavior. See “pvPut” on page 35 and “pvGet” on page 36.

Sequencer deletion re-written

Sequencer deletion has been completely re-written. You can no longer delete a sequencer by deleting one of its tasks. Instead you must use the new **seqStop** routine. See “Stopping the State Program Tasks” on page 26.

efClear can wake up state sets

Clearing an event flag can now wake up state sets that reference the event flag in **when** tests.

More C syntax is supported

The “**to**” in **assign**, **sync** and **syncQ** statements is now optional.

Compound expressions such as **i=1,j=2** (often used in **for** loops) are now permitted.

Variables can now be initialized in declarations such as **int i=2;**.

Pre-processor “**#**” lines are now permitted between state sets and states (relaxes restrictions on using **#include** to include code).

“**~**” (complement) and “**^**” (exclusive or) operators are permitted.

ANSI string concatenation, *e.g.* **"xxx" "yyy"** is the same as **"xxxyyy"**, is supported.

Full exponential representation is supported for numbers (previously couldn’t use “**E**” format).

1.5.3 Bugs fixed

Avoidance of segmentation violations

SEGV no longer occurs if an undeclared variable or event flag is referenced

SEGV no longer occurs if the last bit of an event mask is used

SEGV no longer occurs when doing **seqShow** and there was no previous state

Miscellaneous other problems found by purify were fixed.

Avoidance of race condition which prevented monitors from being enabled

If a connection handler was called before **`seq_pvMonitor`**, a race condition meant that the **`ca_add_array_event`** routine might never get called.

1.5.4 Miscellaneous

Compilation warnings have been avoided wherever possible.

A 60Hz system clock frequency is no longer assumed.

Error reporting is now more consistent; it is currently just using **`errlogPrintf`**.

The new EPICS R3.14 **`configure`**-based make rules are used.

1.6 Future Plans

Several items remain unsupported or only partially supported. Users are encouraged to provide feedback on this list or on other desired items.

Device support

This is partially supported. See “Device support” on page 3.

Local variables

These are partially supported. See “Local variables” on page 4.

pvNew dynamic loading

This would remove some undesirable library dependencies. See “Overview” on page 42.

Hierarchical states

This would be a major enhancement and would, incidentally, bring the sequencer model into very close agreement with the Harel model that is espoused by the UML. Events would be propagated up the state hierarchy.

1.7 Notes on v1.9 Release

With this version (v1.9), we have incorporated many extensions to the state notation language. Some of these changes offer significant advantages for programs and systems with a large number of control system variables.

Number of control system variables

The previous restriction on the number of control system variables that could be defined no longer applies. Only the amount of memory on the target processor limits the number of variables.

Array assignments

Individual elements of an array may be assigned to control system variables. This feature simplifies many codes that contain groups of similar variables. Furthermore, double-subscripted arrays allow arrays of array-valued variables.

Dynamic assignments

Control system variables may now be dynamically assigned or re-assigned within the language at run time.

Hex constants

Hexadecimal numbers are now permitted within the language syntax. Previously, these had to be defined in escaped C code.

Time stamp

The programmer now has access to the time stamp associated with a control system variable.

Pointers

Variables may now be declared as pointers.

seqShow

We enhanced the **`seqShow`** command to present more relevant information about the running state programs.

seqChanShow

The **`seqChanShow`** command now allows specification of a search string on the variable name, permits forward and backward stepping or skipping through the variable list, and optionally displays only variables that are or are not connected.

The syntax for displaying only variables that are not connected is
seqChanShow "<seq_program_name>", "-"

ANSI prototypes

SNC include files now use ANSI prototypes for all functions. To the programmer this means that an ANSI compiler must be used to compile the intermediate C code.

Fix for task deletion

Version 1.8 of the sequencer didn't handle the task deletion properly if a task tried to delete itself. We corrected this in version 1.9.